



**PD-142**

Fixture Number

Job Type

Job Name

Notes~Modifications

## PD-14200~PD-14221

Our Marathon fixtures are quite the conversation topic. We make them for courthouses and some schools and federal buildings. The body of the fixture (the bowl) is solid brass or aluminum. We spin the metal here in the shop on hard white maple molds. The stars are one piece metal stampings. The banding is a continuous piece of rolled filigree. And the fabric is wrapped around non-ferrous rods and tubing for effect. These are exquisite fixtures and can offer the kind of visual response and praise you seldom hear about lighting. We offer them in all brass and aluminum finishes complete with modular LED lamping as well.

### ~Marathon Series~

Chandelier: CH-14201~CH-14215

Pendant: PD-14200~PD-14221

Ceiling Mt: CL-14200~CL-14208

Wall Mt: SC-14200~SC-14211

Bollard: BL-14200~BL-14211

**Mounting:** Lightsmith fixtures mount to standard 4" octagon electrical boxes unless otherwise specified. All hardware and canopies supplied.

**Listing and Warranty:** Lightsmith fixtures are Underwriters Laboratories listed and carry a standard three year warranty against defects in materials and labor beginning at date of shipment.



### Fixture Specifications

**PD-142**

FIXTURE NUMBER  
(Example: PD-14200)

~ **NR**

DIFFUSER  
Not Required

OPTIONS

- L38:** 38wLED R40 Downlight
- L52:** 52wLED R40 Downlight
- L83:** 83wLED R40 Downlight
- DIM:** Dimming Driver (std)
- REM:** Remote Emer.Driver

METAL FINISH  
(Example: ABB)

VOLTAGE  
(120V)  
(277V)  
(347V)

STEM=S+Lgth  
(Example:S-96")  
CABLE=C+Lgth  
(Example:C-96")  
NR=Not required

OPTIONS  
(Example:DIM,REM)

- SPR:** Surge protector
- IEM:** Integral Emer.Ballast

MODIFICATIONS  
(Example:Custom Paint\*)  
Use "Notes" Box At Top To Explain Modifications

Fixture Number	Dimensions	Lamping	Weight	Stem/Chain	Options
<input type="checkbox"/> <b>PD-14209</b>	20w x 18h	4-13wL(5640 lm)	28 lbs	3' Std	L38
<input type="checkbox"/> <b>PD-14210</b>	26w x 24h	6-13wL(8460 lm)	35 lbs	6' Std	L52
<input type="checkbox"/> <b>PD-14211</b>	32w x 29h	8-13wL(11280 lm)	42 lbs	9' Std	L52
<input type="checkbox"/> <b>PD-14212</b>	38w x 35h	10-13wL(14100 lm)	50 lbs	9' Std	L83
<input type="checkbox"/> <b>PD-14213</b>	46w x 42h	12-13wL(16920 lm)	61 lbs	12' Std	L83
 <input type="checkbox"/> <b>PD-14220</b>	 20w x 18h	 4-75wA(4800 lm)	 26 lbs	 3' Std	 IEM,REM,SPR**
 <input type="checkbox"/> <b>PD-14200</b>	 26w x 24h	 6-75wA(7200 lm)	 31 lbs	 6' Std	 L38
 <input type="checkbox"/> <b>PD-14221</b>	 32w x 29h	 8-75wA(9600 lm)	 38 lbs	 9' Std	 L52
 <input type="checkbox"/> <b>PD-14201</b>	 38w x 35h	 10-75wA(12000 lm)	 46 lbs	 9' Std	 L83
 <input type="checkbox"/> <b>PD-14202</b>	 46w x 42h	 12-75wA(14400 lm)	 55 lbs	 12' Std	 L83

~Single Circuit Standard Wiring~

\*\*All LED Fixtures

 <input type="checkbox"/> <b>NA</b>	 <input type="checkbox"/> <b>NA</b>	 <input type="checkbox"/> <b>ECH: Etched*</b>
*Etched option creates a matte, non-glossy finish on one side of the diffuser. (Example:WOA-ECH)		

 <input type="checkbox"/> <b>METAL FINISH</b>	 <b>SOLID BRASS FINISHES</b>	 <b>PAINTED METAL FINISHES</b>	 <b>ALUMINUM FINISHES</b>	 <b>STAINLESS STEEL FINISHES</b>
 <input type="checkbox"/> <b>ABB:</b> Antique Brass	 <input type="checkbox"/> <b>DGP:</b> Dark Green	 <input type="checkbox"/> <b>SAA:</b> Satin Aluminum	 <input type="checkbox"/> <b>NA</b>	
 <input type="checkbox"/> <b>SBB:</b> Satin Brass	 <input type="checkbox"/> <b>VGP:</b> Verde Green	 <input type="checkbox"/> <b>SNA:</b> Satin Nickel		
 <input type="checkbox"/> <b>PBB:</b> Polished Brass	 <input type="checkbox"/> <b>CGP:</b> Charcoal Gray	 <input type="checkbox"/> <b>PAA:</b> Polished Aluminum		
 <input type="checkbox"/> <b>ANB:</b> Antique Nickel	 <input type="checkbox"/> <b>MBP:</b> Medium Bronze	 <input type="checkbox"/> <b>BBA:</b> Burnished Bronze		
 <input type="checkbox"/> <b>SNB:</b> Satin Nickel	 <input type="checkbox"/> <b>SBP:</b> Satin Black	 <input type="checkbox"/> <b>RNA:</b> Red Naval Bronze		
 <input type="checkbox"/> <b>PNB:</b> Polished Nickel	 <input type="checkbox"/> <b>DBP:</b> Dark Bronze	 <input type="checkbox"/> <b>SGA:</b> Satin Gold		
 <input type="checkbox"/> <b>AZB:</b> Antique Bronze	 <input type="checkbox"/> <b>LBP:</b> Light Bronze	 <input type="checkbox"/> <b>SBA:</b> Satin Bronze		
 <input type="checkbox"/> <b>SZB:</b> Satin Bronze	 <input type="checkbox"/> <b>MGP:</b> Medium Gold	 <input type="checkbox"/> <b>ORA:</b> Oil Rubbed Bronze		
 <input type="checkbox"/> <b>PZB:</b> Polished Bronze	 <input type="checkbox"/> <b>SCP:</b> Sponged Copper	 <input type="checkbox"/> <b>SCA:</b> Satin Copper		
 <input type="checkbox"/> <b>CSB:</b> Custom Brass*	 <input type="checkbox"/> <b>CSP:</b> Custom Paint*	 <input type="checkbox"/> <b>CSA:</b> Custom Aluminum*		

 <input type="checkbox"/> <b>OPTIONS</b>	 <b>L38:</b> 38wLED R40 Downlight	 <input type="checkbox"/>	 <b>SPR:</b> Surge protector
 <input type="checkbox"/> <b>L52:</b> 52wLED R40 Downlight	 <input type="checkbox"/>	 <input type="checkbox"/> <b>IEM:</b> Integral Emer.Ballast	
 <input type="checkbox"/> <b>L83:</b> 83wLED R40 Downlight	 <input type="checkbox"/>		
 <input type="checkbox"/> <b>DIM:</b> Dimming Driver (std)	 <input type="checkbox"/>		
 <input type="checkbox"/> <b>REM:</b> Remote Emer.Driver	 <input type="checkbox"/>		