

<u>Lambert</u>

3301-PT~3316-PT

Our Lambert fixtures are keen blends of old and new symbols. They feature Christian "sign of the fish" details at bottom as well contemporary tapered as crosses above. Tall vertical spindles at top are capped by a square aesthetic loop above in the chain suspended version. These are beautiful and bright lanterns meant to lighten up any sanctuary with their Christian symbolism as well as their actual physical brightness. We really enjoy building them. Tight constructions and ultimate good looks make them a pleasure to create. Many lamping and finish options are available.

~Lambert Series~

Chandelier:3341-CHT~3372-CHT

Pendant:3301-PT~3316-PT

Ceiling Mt:3304-CT~3317-CT

Wall Mt:3301-WT~3313-WT

S-Pendant:3303-ST~3315-ST

Mounting:Lightsmith fixtures mount to standard 4" octagon electrical boxes unless otherwise specified. All hardware and canopies supplied.

Listing and Warranty: Lightsmith fixtures are Underwriters Laboratories listed and carry a standard three year warranty against defects in materials and labor beginning at date of shipment.













DIFFUSER (Example: BGA-ECH)





Notes~Modifications

				·		
	Fixture Number	Dimensions	<u>Lamping</u>	Weight	Stem/Chain	Options
LED	3301-PT	10w x 27h	2-13wL(2820 lm)	26 lbs	3' Std	IEM,REM,SPR**
	3302-PT	12w x 33h	4-13wL(5640 lm)/1-38wC(5734 lm)	32 lbs	6' Std	L313
	3303-PT	14w x 38h	6-13wL(8460 lm)/1-38wC(5734 lm)	38 lbs	9' Std	L313
	3304-PT	16w x 44h	12-13wL(16920 lm)/1-52wC(9375 lm)	51 lbs	9' Std	L323
	3305-PT	18w x 49h	12-13wL(16920 lm)/1-83wC(12597 lm)	70 lbs	12' Std	L323
INCANDESCENT	☐ 3308-PT	10w x 27h	1-150 wA (1200 lm)	23 lbs	3' Std	L38
	3310-PT	12w x 33h	3-75wA(3600 lm)/1-250wP38(3600 lm)	27 lbs	6' Std	L52,L310
	3312-PT	14w x 38h	6-75wA(7200 lm)/1-250wP38(3600 lm)	35 lbs	9' Std	L52,L610
	3314-PT	16w x 44h	6-75wA(7200 lm)/1-500wR40(5000 lm)	48 lbs	9' Std	L83,L610
	3316-PT	18w x 49h	9-75 wA (10800 lm)/1-500 w R40(5000 lm)	62 lbs	12' Std	L83,L910
FLUORESCENT			To Comb Obs. Let Web.			MANUEDE

		Two Circuits Standard Wiring~		**All LED Fixtures
DIFFUSER	BGA: Beige Alabaster Acrylic NHA: Natural Horn Acrylic WHA: White Alabaster Acrylic HNA: Honey Alabaster Acrylic WOA: White Opal Acrylic	GRA: Green Edge A EGA: Earth Green A DGA: Deep Gold Ac SOG: Streaked Opa WOG: White Opal G	Acrylic *Etcheo crylic matte, one sid Il Glass (Examp	CH: Etched* d option creates a non-glossy finish on le of the diffuser. ole:WOA-ECH)
(METAL FINISH)	ABB: Antique Brass SBB: Satin Brass PBB: Polished Brass ANB: Antique Nickel SNB: Satin Nickel PNB: Polished Nickel AZB: Antique Bronze SZB: Satin Bronze PZB: Polished Bronze SCF	P: Dark Green P: Verde Green P: Charcoal Gray P: Medium Bronze P: Satin Black P: Dark Bronze P: Light Bronze P: Medium Gold P: Sponged Copper	ALUMINUM FINISHES AA: Satin Aluminum NA: Satin Nickel AA: Polished Aluminum BA: Burnished Bronze NA: Red Naval Bronze GA: Satin Gold BA: Satin Bronze RA: Oil Rubbed Bronze CA: Satin Copper SA: Custom Aluminum*	STAINLESS STEEL FINISHES NA O O O O O O O O O O O O O
OPTIONS	L38: 38wLED R40 Downlight L52: 52wLED R40 Downlight L83: 83wLED R40 Downlight DIM: Dimming Driver (std) REM: Remote Emer.Driver	L313: 3-13wCLED Upl L323: 3-23wCLED Upl L310: 3-10wLED A-lan L610: 6-10wLED A-lan L910: 9-10wLED A-lan	ight IEM: Ir	Surge protector ntegral Emer.Ballast
~	METAL FINISH (Example: ABB) VOLTAGE (120V)		OPTIONS mple:DIM,REM)	MODIFICATIONS (Example:Custom Paint*)

CHAIN=C+Lgth

(Example:C-96'

NR=Not required



Use "Notes" Box At Top To

Explain Modifications

(277V)

(347V)